



Item	Part No.	Description	Item	Part No.	Description
1	300020	Filter Choke (L1)	36	82443	39,000 ohms \pm 10% $\frac{1}{2}$ W. (R29)
2	300002	Locating Pin	37	82443	39,000 ohms \pm 10% $\frac{1}{2}$ W. (R28)
3	86121	.1 mfd. \pm 10% 600 V. (C17)	38	86116	.001 mfd. \pm 10% 100 V. (C3)
4	86070	.01 mfd. \pm 10% 1000 V. (C19)	39	86116	.001 mfd. \pm 10% 100 V. (C5)
5	82674	10,000 ohms \pm 5% $\frac{1}{2}$ W. (R22)	40	86116	.001 mfd. \pm 10% 100 V. (C4)
6	300007	4 prong Plug (P1)	41	300072	Treble Control Switch (SW1)
7	86121	.1 mfd. \pm 10% 600 V. (C18)	42	82666	100,000 ohms \pm 5% $\frac{1}{2}$ W. (R4)
8	302038	4 lug Terminal Strip	43	300039	4 lug Terminal Strip
9	81084	125 ohms \pm 10% W. W. 5 W. (R23)	44	84263	Octal Socket (6J7)
10	84261	Octal Socket (6L6G)	45	87564	20 mfd. 25 V. Lytic (C8)
11	82675	82,000 ohms \pm 5% $\frac{1}{2}$ W. (R20)	46	82420	470 ohms \pm 10% $\frac{1}{2}$ W. (R5)
12	82109	330 ohms \pm 20% $\frac{1}{2}$ W. (R32)	47	82454	.33 megohm \pm 10% $\frac{1}{2}$ W. (R27)
13	82109	330 ohms \pm 20% $\frac{1}{2}$ W. (R31)	48	86120	.02 mfd. \pm 20% 400 V. (C7)
14	10070	2 lug Terminal Strip	49	82453	.27 megohm \pm 10% $\frac{1}{2}$ W. (R26)
15	85083	1000 mmfd. \pm 15% Mica (C6)	50	82418	330 ohms \pm 10% $\frac{1}{2}$ W. (R25)
16	86120	.02 mfd. \pm 20% 400 V. (C20)	51	82424	1000 ohms \pm 10% $\frac{1}{2}$ W. (R9)
17	86119	.1 mfd. \pm 10% 100 V. (C15)	52	82753	4700 ohms \pm 10% 1 W. (R16)
18	300040	Input Transformer (T2)	53	84262	Octal Socket (6SN7)
19	302026	Spacer	54	82130	1 megohm \pm 20% $\frac{1}{2}$ W. (R8)
20	84200	7 prong Socket (Spkr.) (S5)	55	300008	6 prong Socket (S1)
21	82458	.68 megohm \pm 10% $\frac{1}{2}$ W. (R2)	56	300060	4 lug Terminal Strip
22	82464	2.2 megohms \pm 10% $\frac{1}{2}$ W. (R3)	57	84264	Octal Socket (9U4G)
23	86116	.001 mfd. \pm 10% 100 V. (C2)	58	82430	3300 ohms \pm 10% $\frac{1}{2}$ W. (R13)
24	82465	2.7 megohms \pm 10% $\frac{1}{2}$ W. (R1)	59	500061	Fuse Receptacle
25	85079	250 mmfd. \pm 10% Mica (C1)	60	300103	2 Amp. Fuse (3AG)
26	84203	5 prong Socket (P. L.) (S2)	61	100069	3 lug Terminal Strip
27	86115	.5 mfd. \pm 10% 100 V. (C16)	62	82437	.56 megohms \pm 10% $\frac{1}{2}$ W. (R6)
28	82418	330 ohms \pm 10% $\frac{1}{2}$ W. (R10)	63	86117	.1 mfd. \pm 20% 400 V. (C9)
29	82422	680 ohms \pm 10% $\frac{1}{2}$ W. (R11)	64	82434	6800 ohms \pm 10% $\frac{1}{2}$ W. (R17)
30	82457	.56 megohms \pm 10% $\frac{1}{2}$ W. (R15)	65	82746	1000 ohms \pm 10% 1 W. (R19)
31	84265	7 prong Socket, Large (S3)	66	82813	10,000 ohms \pm 10% 2 W. (R18)
32	82428	2200 ohms \pm 10% $\frac{1}{2}$ W. (R12)	67	82640	27,000 ohms \pm 5% $\frac{1}{2}$ W. (R7)
33	300073	Bass Control Switch (SW2)	68	82674	10,000 ohms \pm 5% $\frac{1}{2}$ W. (R21)
34	82443	39,000 ohms \pm 10% $\frac{1}{2}$ W. (R30)	69	302037	4 lug Terminal Strip
35	301021	4 lug Terminal Strip	70	82675	82,000 ohms \pm 5% $\frac{1}{2}$ W. (R24)
			71	300005	Chassis and Grommet Assembly

FIG. 3a