

WIRED SELECTION RECEIVER, TYPE WSR7-L6

(Preceding Page)

PARTS LIST

Item	Part No.	Part Name	Item	Part No.	Part Name
C1	87571	25 mfd. 50 v. Electrolytic	K2	303391	Unit Step Relay
C3	11076	5.0 mfd. 300 v. Condenser	K3	303392	Pawl Release Magnet
C4	87611	300 mfd. 50 v. Electrolytic	K4	303077	Play Control Relay
C5	86009	.05 mfd. 200 v. Condenser	K5	303074	Transfer Relay
C6	86009	.05 mfd. 200 v. Condenser	K6	303255	Timing Relay No. 2
C7	86009	.05 mfd. 200 v. Condenser	K7	303075	Timing Relay No. 1
C8	86009	.05 mfd. 200 v. Condenser	K8	400664	Credit Solenoid
C9	86009	.05 mfd. 200 v. Condenser	K9	400664	Credit Solenoid
C10	86009	.05 mfd. 200 v. Condenser	K10	400664	Credit Solenoid
CR1	400587	Selenium Rectifier	K11	400685	Cancel Solenoid
C12	86069	.005 mfd. 1000 v. Condenser	K12	400696	Timing Relay Assembly
C13	86173	.01 mfd. 200 v. Condenser	P1	303334	Line Cord & Plug Assembly
C14	86173	.01 mfd. 200 v. Condenser	P2	303080	27 Prong Plug
C15	86173	.01 mfd. 200 v. Condenser	P3	400695	Octal Plug
E1	303361	Terminal Strip	R1	82448	.1 meg 10% 1/2 w. Resistor
E2	303363	Terminal Strip	R2	82436	10,000 ohm 10% 1/2 w. Resistor
E3	303365	Terminal Strip	R3	82444	47,000 ohm 10% 1/2 w. Resistor
F1	602411	5 amp. Fuse, 3 AG	R4	82764	47 ohm 10% 1 w. Resistor
F2	303257	3 amp. Fuse, 3 AG	R5	81169	1 ohm w.w. 4 w. Resistor
F3	301205	3 amp. Fuse, Fustal	R6	82403	18 ohm 10% 1/2 w. Resistor
F4	303275	1 amp. Fuse, Sto-Blo	R7	81169	1 ohm w.w. 4 w. Resistor
J1	12006	3 Contact Socket	R8	82432	4700 ohm 10% 1/2 w. Resistor
J2	11401	A.C. Socket	S1	303112	Toggle Switch
J3	301020	4 Contact Socket	S2	303115	Transfer Switch
J5	84244	9 Contact Socket	S3	400686	Cam Switch Assembly
J6	301019	2 Contact Socket	S4	400589	Timing Relay Switch
J7	303253	11 Contact Socket	S5	400665	Credit Switch Assembly
J8	84283	5 Contact Socket	S6	400671	Manual Credit Switch
J9	11202	27 Contact Socket	T1	303340	Power Transformer
J10	84292	Octal Socket	T2	303342	25 v. Transformer
J11	84293	Small 4 Contact Socket	Z1	303370	Step Switch & Relay Assembly
J12	84292	Octal Socket	Z2	303390	Step Switch Assembly
K1	303393	Group Step Relay	Z3	400640	Credit & Cancel Assembly