

STEREO HIGH FIDELITY AMPLIFIER, Type SHFA1

Item	Part No.	Part Name			Item	Part No.	Part Name		
R124	82793	68K	± 5%	½ Watt	R187	82630	6.8K	± 5%	½ Watt
R125	82630	6.8K	± 5%	½ Watt	R188	82470	6.8 MEG	± 10%	½ Watt
R126	82470	6.8 MEG	± 10%	½ Watt	R189	82506	22 MEG	± 10%	½ Watt
R127	82449	120K	± 10%	½ Watt	R190	82449	120K	± 10%	½ Watt
R128	82506	22 MEG	± 10%	½ Watt	R191	82666	100K	± 5%	½ Watt
R129	82666	100K	± 5%	½ Watt	R192	82891	Pec. 6 Resistors		
R130	82891	Pec. 6 Resistors			R193	82798	360	± 5%	½ Watt
R131	82798	360	± 5%	½ Watt	R194	82425	1.2K	± 10%	½ Watt
R132	82425	1.2K	± 10%	½ Watt	R195	82695	56K	± 5%	½ Watt
R133	82695	56K	± 5%	½ Watt	R196	82691	200K	± 5%	½ Watt
R134	82691	200K	± 5%	½ Watt	R197	82890	Pec. 5 Resistors		
R135	82890	Pec. 5 Resistors			R198	82418	330	± 10%	½ Watt
R136	82464	2.2 MEG	± 10%	½ Watt	R199	82464	2.2 MEG	± 10%	½ Watt
R137	82421	560	± 10%	½ Watt	R200	82421	560	± 10%	½ Watt
R138	82446	68K	± 10%	½ Watt	R201	82446	68K	± 10%	½ Watt
R139	82418	330	± 10%	½ Watt	R202	82425	1.2K	± 10%	½ Watt
R140	82425	1.2K	± 10%	½ Watt	R203	82426	7.5K	± 5%	½ Watt
R141	305624	Dual Volume Control			R204	82631	1.5K	± 5%	½ Watt
R142	82426	7.5K	± 10%	½ Watt	R205	82425	1.2K	± 10%	½ Watt
R143	82631	1.5K	± 5%	½ Watt	R206	82424	1.0K	± 10%	½ Watt
R144	82425	1.2K	± 10%	½ Watt	R207	82430	3.3K	± 10%	½ Watt
R145	82424	1.0K	± 10%	½ Watt	R208	82408	47	± 10%	½ Watt
R146	82430	3.3K	± 10%	½ Watt	R209	82631	7.5K	± 5%	½ Watt
R147	305623	Dual Balance Pot.			R210	82437	12K	± 10%	½ Watt
R148	82437	12K	± 10%	½ Watt	R211	82444	47K	± 10%	½ Watt
R149	82456	470K	± 10%	½ Watt	R212	82431	3.9K	± 10%	½ Watt
R150	82440	22K	± 10%	½ Watt	R213	82456	470K	± 10%	½ Watt
R151	82659	330	± 5%	½ Watt	R214	82440	22K	± 10%	½ Watt
R152	82433	5.6K	± 10%	½ Watt	R215	82659	330	± 5%	½ Watt
R153	82667	470K	± 5%	½ Watt	R216	82433	5.6K	± 10%	½ Watt
R154	81198	3000	± 10%	10 Watt	R217	82667	470K	± 5%	½ Watt
R155	81199	25K	± 10%	10 Watt	R218	82457	560K	± 10%	½ Watt
R156	82457	560K	± 10%	½ Watt	R219	82629	5.6K	± 5%	½ Watt
R157	82629	5.6K	± 5%	½ Watt	R220	82789	390K	± 5%	½ Watt
R158	82789	390K	± 5%	½ Watt	R221	82433	5.6K	± 10%	½ Watt
R159	82433	5.6K	± 10%	½ Watt	R222	82789	390K	± 5%	½ Watt
R160	82789	390K	± 5%	½ Watt	R223	82667	470K	± 5%	½ Watt
R161	82701	2.7K	± 10%	1 Watt	R224	82667	470K	± 5%	½ Watt
R162	82439	18K	± 10%	½ Watt	R225	305674	1500 Tap Resistor		
R163	82667	470K	± 5%	½ Watt	S101	305621	Treble Switch 4P6T		
R164	82667	470K	± 5%	½ Watt	S102	305622	Bass Switch 4P4T		
R165	82637	15K	± 5%	½ Watt	S103	305625	Speaker Switch 2P5T		
R166	82637	15K	± 5%	½ Watt	S104	305635	Mute Left Switch		
R167	82637	15K	± 5%	½ Watt	S105	305635	Mute Right Switch		
R168	82630	6.8K	± 5%	½ Watt	T101	305619	Power Transformer		
R169	82618	100	± 5%	½ Watt	T102	305617	Audio Output		
R170	82616	220K	± 5%	½ Watt	T103	305618	Audio Output		
R171	82697	20K	± 5%	½ Watt	TB101-102				
R172	82640	27K	± 5%	½ Watt	602815	Terminal Board			
R173	82637	15K	± 5%	½ Watt	V101, V103				
R174	82670	2.7K	± 5%	½ Watt	308120	12AX7			
R175	82847	68K	± 5%	2 Watt	V102	308603	6BJ6		
R176	82456	470K	± 10%	½ Watt	V104	308120	12AX7		
R177	82616	220K	± 5%	½ Watt	V105 - 106				
R178	82698	150K	± 5%	½ Watt	308026	6973			
R179	82610	6.2K	± 5%	½ Watt	V107	308603	6BJ6		
R180	82421	560	± 10%	½ Watt	V108 - 109				
R181	82422	680	± 10%	½ Watt	308120	12AX7			
R182	82635	12K	± 5%	½ Watt	V110	308120	12AX7		
R183	82640	27K	± 5%	½ Watt	V111 - 112				
R184	82460	1 MEG	± 10%	½ Watt	308026	6973			
R185	82470	6.8 MEG	± 10%	½ Watt	V113	308506	5U4GB		
R186	82793	68K	± 5%	½ Watt					