

STEREO HIGH FIDELITY AMPLIFIER, Type SHFA5

PARTS LIST

Item	Part No.	Description	Item	Part No.	Description	Item	Part No.	Description	Item	Part No.	Description
C101	87697	9 mfd. 6 V. Lytic	C138	86140	0.05 mfd. 10% 400 V. Paper	R118	82459	820,000 ohm	R156	82696	270,000 ohm 5%
C102	87696	50 mfd. 6 V. Lytic	C139	86289	3.3 mfd. 500 V. Ceramic	R119	82423	820 ohm	R157	82696	270,000 ohm 5%
C103	86327	0.047 mfd. 10% 50 V. Mylar	C140	86146	0.05 mfd. 10% 600 V. Paper	R120	82452	220,000 ohm	R158	82638	18,000 ohm 5%
C104	86334	0.1 mfd. 10% 50 V. Mylar	C141	86146	0.05 mfd. 10% 600 V. Paper	R121	82811	15,000 ohm 2 W. 5%	R159	82641	30,000 ohm 1/2 W. 5%
C105	86327	0.047 mfd. 10% 50 V. Mylar	C142	86243	150 mfd. 500 V. Ceramic	R122	82811	15,000 ohm 2 W. 5%	R160	82641	30,000 ohm 1/2 W. 5%
C107	86332	0.0068 mfd. 10% 50 V. Mylar	C143	87710	200 mfd. -15 +40% Lytic	R123	82696	270,000 ohm 5%	R161	82642	33,000 ohm 1/2 W. 5%
C108	86326	0.01 mfd. 50 V. Mylar	C144	86313	0.01 mfd. 500 V. Ceramic	R124	82696	270,000 ohm 5%	R162	82642	33,000 ohm 1/2 W. 5%
C109	86327	0.047 mfd. 10% 50 V. Mylar	C145	86313	0.01 mfd. 500 V. Ceramic	R125	82638	18,000 ohm 5%	R163	82448	100,000 ohm 1/2 W. 10%
C110	86140	0.05 mfd. 10% 400 V. Paper	C146	86313	0.01 mfd. 500 V. Ceramic	R126	82869	12,000 ohm 1 W. 10%	R164	82460	1 megohm
C111	86332	0.0068 mfd. 10% 50 V. Mylar	CR101	309390	Selenium Diode	R127	81213	2,000 ohm 3 W.	R165	82612	2,000 ohm 1/2 W. 5%
C112	86309	0.001 mfd. 10% 500 V. Ceramic	CR102	309399	Selenium Diode	R128	81199	25,000 ohm 10 W.	R166	82612	2,000 ohm 1/2 W. 5%
C113	86340	0.003 mfd. 10% 500 V. Ceramic	CR103	309398	Selenium Diode	R129	81173	100 ohm 7 W.	R167	82460	1 megohm
C114	86212	0.01 mfd. 10% 400 V. Paper	CR104	309397	Selenium Diode	R130	82634	10,000 ohm 5%	R168	82448	100,000 ohm 1/2 W. 10%
C115	86140	0.05 mfd. 10% 400 V. Paper	J 101	12034	Input Socket	R131	82620	1,000 ohm 5%	R169	82430	3,300 ohm 1/2 W. 10%
C116	86289	3.3 mfd. 500 V. Ceramic	J 102	84283	Mute Squelch 5 Pin	R132	82626	3,900 ohm 5%			
C117	86146	0.05 mfd. 10% 600 V. Paper	P101	300007	Power Input	R133	82418	330 ohm			
C118	86146	0.05 mfd. 10% 600 V. Paper	P102	803725	D.S. Speaker Plug	R134	305833	Balance Control (1 meg)	S 101	305830	Bass Range 2P3T
C119	86243	150 mfd. 500 V. Ceramic	Q101	309404	2N591 Transistor	R135	308962	12,000 ohm 5%	S 102	305830	Treble Range 2P3T
C120A	87689	20 mfd. 400 V. Lytic	Q102	309404	2N591 Transistor	R136	308961	220,000 ohm 5%			
C120B	87689	40 mfd. 400 V. Lytic	R101	308962	12,000 ohm 5%	R137	82556	150 ohm 5%			
C120C	87689	40 mfd. 400 V. Lytic	R102	308961	220,000 ohm 5%	R138	82626	3,900 ohm 5%			
C120D	87689	40 mfd. 450 V. Lytic	R103	82656	150 ohm 5%	R139	82695	56,000 ohm 5%			
C121	87691	50 mfd. 60 V. Lytic	R104	82626	3,900 ohm 5%	R140	82625	3,600 ohm 5%	T101	305814	Power Transformer
C122A	87715	20 mfd. 75 V. Lytic	R105	82695	56,000 ohm 5%	R141	82676	47,000 ohm 5%	T102	305914	Audio Transformer
C122B	87715	50 mfd. 75 V. Lytic	R106	82625	3,600 ohm 5%	R142	82452	220,000 ohm 10%	T103	305915	Audio Transformer
C124	87697	9 mfd. 6 V. Lytic	R107	82676	47,000 ohm 5%	R143	82448	100,000 ohm	TB101	305832	Terminal Board 9 Lugs
C125	87696	50 mfd. 6 V. Lytic	R108	82676	47,000 ohm 5%	R144	82671	1,300 ohm 5%	TB102	305913	Terminal Board 4 Lugs
C126	86327	0.047 mfd. 10% 50 V. Mylar	R109	82448	100,000 ohm	R145	82666	100,000 ohm 5%			
C127	86334	0.1 mfd. 10% 50 V. Mylar	R110	82671	1,300 ohm 5%	R146	82441	27,000 ohm	V101	308646	6EU7
C128	86327	0.047 mfd. 10% 50 V. Mylar	R111	82666	100,000 ohm. 5%	R147	82441	27,000 ohm	V102	308647	7199
C130	86332	0.0068 mfd. 10% 50 V. Mylar	R112	82441	27,000 ohm	R148	82616	220,000 ohm 5%	V103	308026	6973
C131	86326	0.01 mfd. 50 V. Mylar	R113	82441	27,000 ohm	R149	82449	120,000 ohm	V104	308026	6973
C132	86327	0.047 mfd. 50 V. Mylar	R114	305821	Volume Control 1 meg ea. s.c.	R150	82460	1 megohm	V105	308026	6973
C133	86140	0.05 mfd. 10% 400 V. Paper	R115	82616	220,000 ohm 5%	R151	82459	820,000 ohm	V106	308647	7199
C134	86332	0.0068 mfd. 10% 50 V. Mylar	R116	82449	120,000 ohm	R152	82423	820 ohm	V107	308026	6973
C135	86309	0.001 mfd. 10% 500 V. Ceramic	R117	82460	1 megohm	R153	82452	220,000 ohm	V108	308026	6973
C136	86340	0.003 mfd. 10% 500 V. Ceramic				R154	82811	15,000 ohm 2 W. 5%	V109	308506	5U4GB
C137	86212	0.01 mfd. 10% 400 V. Paper				R155	82811	15,000 ohm 2 W. 5%			